



IECEX Certificate of Conformity

INTERNATIONAL ELECTROTECHNICAL COMMISSION IEC Certification Scheme for Explosive Atmospheres

for rules and details of the IECEx Scheme visit www.iecex.com

Certificate No.: **IECEX ITS 05.0002** Issue No.: **0**

Status: **Current**

Date of Issue: **2005-01-27** Page 1 of 3

Applicant: **BEKA Associates Limited**
Old Charlton Road
Hitchin
Herts
SG5 2DA
United Kingdom

Electrical Apparatus: **BA 307C Loop Powered 3½ Digit Indicator**
Optional accessory:

Type of Protection: **Intrinsic Safety**

Marking: **Ex ia IIC T5**
Ta = -40°C to 60°C


Approved for issue on behalf of the IECEx
Certification Body:

R M Adams

Position:

Certification Manager

Signature:
(for printed version)


2005-03-09

Date:

1. This certificate and schedule may only be reproduced in full.
2. This certificate is not transferable and remains the property of the issuing body.
3. The Status and authenticity of this certificate may be verified by visiting the Official IECEx Website.

Certificate issued by:

Intertek Testing & Certification Ltd
ITS House, Cleeve Road,
Leatherhead,
Surrey, KT22 7SB
United Kingdom

Intertek ETL SEMKO
Testing everywhere for markets anywhere.



IECEx Certificate of Conformity

Certificate No.: **IECEx ITS 05.0002**

Date of Issue: **2005-01-27**

Issue No.: **0**

Page **2** of **3**

Manufacturer: **BEKA Associates Limited**
Old Charlton Road
Hitchin
Herts
SG5 2DA
United Kingdom

Manufacturing location(s):

This certificate is issued as verification that a sample(s), representative of production, was assessed and tested and found to comply with the IEC Standard list below and that the manufacture's quality system, relating to the Ex products covered by this certificate, was assessed and found to comply with the IECEx Quality system requirements. This certificate is granted subject to the conditions as set out in IECEx Scheme Rules, IECEx 02 and Operational Documents as amended.

STANDARDS:

The electrical apparatus and any acceptable variations to it specified in the schedule of this certificate and the identified documents, was found to comply with the following standards:

IEC 60079-0 : 2000 Edition: 3.1	Electrical apparatus for explosive gas atmospheres - Part 0: General requirements
IEC 60079-11 : 1999 Edition: 4	Electrical apparatus for explosive gas atmospheres - Part 11: Intrinsic safety 'i'

*This Certificate **does not** indicate compliance with electrical safety and performance requirements other than those expressly included in the Standards listed above.*

TEST & ASSESSMENT REPORTS:

A sample(s) of the equipment listed has successfully met the examination and test requirements as recorded in

IECEx ATR:
UK/ITS/05/04014952A

File Reference:
04014952
02006736



IECEx Certificate of Conformity

Certificate No.: IECEx ITS 05.0002

Date of Issue: 2005-01-27

Issue No.: 0

Page 3 of 3

Schedule

EQUIPMENT:

Equipment and systems covered by this certificate are as follows:

THE BA307C Loop Powered 3½ Digit Indicator is a two wire apparatus designed to be connected in a 4/20 mA process loop and provide a display in engineering units.

The BA307C 3½ Digit Indicator may alternatively be identified as a DA4-Ex/60 or GSI 07 Loop Powered 3½ Digit Indicator

The BA307C is a panel mounting indicator comprising a main board and a display board and an optional root extractor board or a calibrator board and may additionally fitted with an optional back light board, all housed within a metallic enclosure. The enclosure provides a Degree of Protection of at least IP20

Intrinsic safety is assured by limitation of voltage, current and power, limitation of capacitance, suppression of inductance, and infallible segregation.

The equivalent resistance of the apparatus at terminals 1 and 3 is 14.85 Ω minimum in normal operation and 24.75 Ω minimum under fault conditions.

The maximum intrinsically safe input parameters are as follows:

Terminals 1 and 3

$U_i = 30$ V dc

$I_i = 200$ mA

$P_i = 0.85$ W

Terminals 12 and 13 (Separately powered back light)

$U_i = 28$ V

$I_i = 110$ mA

$P_i = 0.77$ W

The equivalent parameters of the apparatus are:

Terminals 1 and 3

$C_i = 0.02$ μ F

$L_i = 0.01$ mH

Terminals 12 and 13

$C_i = 0.045$ μ F

$L_i = 0.02$ mH

Terminals 1 and 13 (Indicator connected to loop powered back light- terminals 3 and 12 connected in series)

$C_i = 0.04$ μ F

$L_i = 0.03$ mH

For intrinsic safety considerations, under fault conditions, the voltage, current and power at terminals 1 and 3 do not exceed those specified in Clause 5.4 of IEC 60079-11:1999. The equivalent capacitance and inductance are the result of r.f. suppression components directly connected to the apparatus terminals.

Variation 0.1

To permit the use of a larger display board than the BA307C to form a BA308C 3½ DIGIT INDICATOR.

The BA308C 3½ Digit Indicator may alternatively be identified as a DA4-Ex/65 or GSI 08 Loop Powered 3½ Digit Indicator